filtemc

AC 3-Phase 4-Line Filters

FT420-4200 Series

Introduction

- Rated current:0.5A~800A
- Solder lug,stud or terminal block connection(≥250A it is copper bar)
- Optional medical versions(H type)
- Custom specific versons available on request

Features and Benefits

- Suitable for three-phase plus neutral line power supply.
- FT420 series are two-stage common mode high performance three-phase four-line filters.
- FT4200 series are two-stage filters comprising one common mode and one differential mode with enhanced filtering effect of the differential mode interference.
- Excellent common and differential mode filtering effect for interference form 10KHz to 30MHz.

Typical Applications

Machine tools

Automation equipment

Power inverter

Medical device and other electric applications requiring higher filtering effect with three-phase and neutral power supply

Electrical Schematics



FT420



FT4200

Technical Date

Rated Voltage: VR	440VAC
Operating Frequency: FR	50/60Hz
Rated Current: IR	0.5~800A@40℃
Test Voltage: Vtest	2250VDC, 3S(line-line); 1760VDC, 3S(line-neutral); 2700VDC, 3S(line-ground);
Climatic Category (IEC 60068-1)	25/085/21(-25℃/+85℃ Damp heat test for 21 days)

Tabulates

Part No.	Rated Current[A]	Leakage Current[mA] 250VAC/50Hz @20°C	Terminals -S	Terminals -T	Weight [g]
FT420-10	10	< 2.0	M4	○	1150/1300
FT420-20	20	< 2.0	M4	○	1200/1400
FT420-30	30	< 6.0	M6	○	1750/1900

Part No.	Rated Current[A]	Leakage Current[mA] 250VAC/50Hz @20°C	Terminals		Weight [g]
			-S	-T	
FT420-40	40	< 6.0	M6	○	1800/1800
FT420-50	50	< 6.0	M6	○	3100/3200
FT420-80	80	< 10.0	M8	○	3200/3700
FT420-100	100	< 10.0	M8	○	3150/5050
FT420-150	150	< 10.0	M10	○	7000/8200
FT420-200	200	< 10.0	M10	○	6500/12350
FT4200-6	6	< 2.0	M4	○	600/800
FT4200-10	10	< 2.0	M4	○	650/600
FT4200-20	20	< 6.0	M4	○	1250/1450
FT4200-30	30	< 6.0	M6	○	2550/1500
FT4200-50	50	< 6.0	M6	○	3000/3100

Insertion Loss(dB)

Common Mode

Differential Mode

Note： Insertion loss is tested with a system of empty load and 50 Ω-50Ω according to UL1283 Standard.The actual effect please follow the field data of real application.

















Outline Drawing and Dimensions(mm)



FT420-10



FT420-20 FT4200-20



FT420-30 FT4200-30



FT420-40



FT420-50 FT4200-50



FT420-80/100



FT420-150



FT420-200



FT4200-6



FT4200-10

Outline Drawing and Dimensions of Terminal Block Series(mm)



FT420-10/20/30-T4 FT4200-20/30-T4



FT420-40-T4



FT420-50-T4



FT420-80-T4



FT420-100-T4



FT420-150-T4



FT420-200-T4



FT4200-6/10-T4



FT4200-50-T4

Important Notes on EMI Filter Application

1. Storage of EMI Filters:

EMI filters mustn't be left out in the heat of the sun or exposed to the rain, it should be stored in warehouse with good ventilation, surrounding temperature between -30 ℃ and +65 ℃, the highest relative air humidity lower than 90%, and no corrosive liquid or gas.

2. Installation of EMI Filters:

- EMI filters should be installed at power input, and the line inside the chassis be as short as possible to reduce radiated interference.
- Both input and output lines of EMI filters neither be intersected nor be tied up by string.
- Make sure the mounting flange fully grounded, and keep the ground cable as short as possible if filters are connected to other equipment.
- If the terminal is stud, please use two spanners to fasten the screw nut when connecting to avoid stud rotating and thus causing changes to the internal circuit and consequently leading to filters arcing, short circuit, broken down or the filtering effect worsened. First use spanner1 to fix the screw nut near the metal case, then use spanner2 to tighten the screw nut in front(shown as Figure1), otherwise the terminals may be damaged. Apply the same for the connection of other phases.
- Keep the tools fastening the stud be vertical to the metal case of filter when installing terminal block filters (shown as Figure2), must not tilt(shown as Figure3), otherwise the terminal blocks may be damaged.



（Figure1）



（Figure2）



（Figure3）

3. Reminding and Warning:

Please read all the safety warnings and instructions before installing filters and putting them into use:

- Don't take terminals as supporting point when moving filters to avoid the terminals distortion, loosening or broken.
- The protective earth connections shall be the first to be made when the EMC filter is installed and the last to be disconnected.
- Filters generate leakage current, please make sure they are well grounded before putting into operation.
- If the rated current is higher than 50A, we recommend grounding by the earth terminals but not only through the metal case of filters.
- Danger of electric shock: EMC filters contain components that store an electric charge. Dangerous voltages can continue to exist at the filter terminals for longer than five minutes even after the power has been switched off.
- The working conditions of EMI filter should comply with the technical parameters stated on the label, over voltage or overload could cause damage to filters. It is suggested to take proper over current protection measures.
- Current drop occurs when the surrounding temperature rises, fail to follow the current drop requirement may lead to impermissible exceeding of the component temperature, as a result the service life of filters will be shortened after long time running.

Service and Support

Contact information of Tech. Dept.:

T: 0086-531-58622887

F: 0086-531-58622899

E: filtemc@filtemc.com

A: Building 20, Xinmao Qilu Science and Technology City, No. 1 Zidong Road, Tianqiao District, Jinan 250119, China

Contact information of Sales:

T: 0086-531-58622888

F: 0086-531-58622886

E: filter@filtemc.com

Skype: Lisawong2016@hotmail.com

Web.: www.filtemc.com